

EVERSE 8

WEATHERIZED BATTERY-POWERED LOUDSPEAKER WITH BLUETOOTH® AUDIO AND CONTROL



Electro-Voice

REAL PRO-AUDIO PERFORMANCE. BATTERY-POWERED CONVENIENCE.



COMPACT & LIGHTWEIGHT

Every detail of EVERSE 8 is designed to maximize easy lifting and transportation – all while reinforcing EV's reputation for real-world durability. An ergonomically designed soft-touch handle and premium lightweight construction make it a breeze to move and mount EVERSE 8. Pack it into the optional tote bag and head out to the gig. It's the all-in-one pro-audio system you can grab to go.



WIRELESS CONTROL & MONITORING

Use the EV QuickSmart Mobile app to adjust all audio, effects and mix functions via your phone or tablet. An intuitive user interface makes it simple to shape your sound to the space, so you can focus on the show.



EXPANDABLE FUNCTIONALITY

The integrated 12 V DC port provides convenient power from the EVERSE 8 battery, perfect for powering a wireless microphone system. Attach the optional accessory tray to the top of your EVERSE 8 to secure receiver hardware in place. A charging port is included for mobile devices if you need a top-up when streaming. Place on a tripod for a longer throw, set long-side-down as a stage monitor, or use upright with the kick-back angle to project up off the performance area. For stereo setups, EVERSE 8 is equipped for Bluetooth® true wireless stereo streaming. Flexible features for a truly self-contained setup, input to output.



POWERED BY DYNACORD

EVERSE 8 is driven by a high-efficiency Class-D amplifier and DSP module developed in collaboration with the world-class audio electronics engineering team at EV's sibling brand Dynacord. Pro features include a built-in four-channel digital mixer with studio-quality effects and processing, 48 V phantom power, feedback suppression and audio ducking. Between the EV and the D badges, you get the best of both worlds.

55°
MONITOR
ANGLE



30°
KICK-BACK
ANGLE



| | | | |
|--|---|--|-------------------------|
| Application | Kick-back / monitor / pole-mounted | | |
| Transducers | 8" woofer, ferrite magnet / 1" titanium dome, neodymium magnet, ferrofluid cooled | | |
| Power rating (peak) | 400 W | | |
| SPL max¹ | 121 dB | | |
| Coverage (H x V) | 100° x 100° | | |
| Frequency range (-10 dB)² / response (-3 dB)³ | 60 Hz-20 kHz / 60 Hz-20 kHz | | |
| Material | Enclosure: polypropylene / grille: steel with black powder coat | | |
| Digital signal processing | QuickSmartDSP features best-in-class processing. Easy setup via seven-band GEQ for main EQ, user-programmable presets, visual monitoring of limiter status, input level control and meters, digital effect control, and master volume control to optimize gain structure, all via LCD or QuickSmart Mobile app. | | |
| Remote control and monitoring | EV QuickSmart Mobile application: quickly and wirelessly configure, control and monitor up to two EVERSE 8 systems simultaneously; and receive immediate notification during critical performance conditions. | | |
| Bluetooth® audio streaming⁴ | <input checked="" type="checkbox"/> | | |
| Crossover frequency | 2250 Hz | | |
| Connectors | 2x XLR/TRS combo jack | 1x 3.5mm stereo | 1x charge port |
| | 1x XLR output | 1x TRS footswitch | 1x 12 V DC power output |
| USB charging | 1.5 A max, device-dependent | | |
| Power consumption⁵ | 100 - 240 V~, 50 - 60 Hz, 0.8 - 0.6 A | | |
| Battery capacity | 86.4 Wh | | |
| Battery at max output⁶ | 6+ hours of run time | | |
| Battery at moderate output⁷ | 12+ hours of run time | | |
| Weight | 16.6 lbs (7.6 kg) | | |
| Dimensions (W x H x D) | 15.75" x 10.83" x 10.71" (400 mm x 275 mm x 272 mm) | | |
| Colors | Black and white | | |
| Accessories | EVERSE8-TRAY-B mic receiver tray black EVERSE8-TRAY-W mic receiver tray white EVERSE8-RAINCVR rain cover | EVERSE8-BAT-B battery pack black EVERSE8-BAT-W battery pack white | |

EV QuickSmart Mobile available in select countries. Apple, the Apple logo, iPhone®, iPad®, and App Store® are trademarks of Apple Inc., registered in the U.S. and other countries. Google Play and the Google Play logo are trademarks of Google LLC. EVERSE 8 is available in select countries. ¹ Maximum SPL is measured at 1 m using broadband pink noise at maximum output. ² Half-space measurement. ³ Full space measurement using music DSP preset. ⁴ Two EVERSE 8 loudspeakers are required for true wireless stereo via a Bluetooth® connection. The Bluetooth word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Bosch Security Systems, LLC is under license. ⁵ Current rating is 1/8 power. ⁶ Maximum output before loudspeaker limit indication, with typical program material. ⁷ Moderate output is approximately 95 dB SPL, with typical program material. ©2022 Bosch Security Systems, LLC